

Airport **Lighting** Company
An ISO 9001:2015 Certified Company

OWNER'S MANUAL



Medium Intensity Elevated Edge Light

L-861

L-861T

L-861E



AirportLightingCompany

An ISO 9001:2015 Certified Company

Medium Intensity Elevated Edge Light

L-861/L-861T/ L-861E

Owner's Manual

ETL Certified Conformance with:
Certified to FAA AC 150/5345-46 (Current Edition)



Manufactured by:
Airport Lighting Company
108 Fairgrounds Drive
Manlius, New York 13104
(315) 682-6460

Email: info@airportlightingcompany.com
Website: www.airportlightingcompany.com



Medium Intensity Runway/Taxiway Light



Compliances (Current Editions)

FAA: AC 150/5345-46, ETL Certified



Application

Taxiway Edge, Runway Edge, Apron Edge, Threshold/End Non Precision Instrument Flight Rules, Displaced Threshold

Key Features

- ETL Certification ensures performance
- One piece housing for easy leveling
- Durable powder coat finish lasts longer
- Threaded 1.5" frangible coupling or optional 2" matches existing baseplates/stakes
- Actual average lamp life far exceeds 1000 hour rated life for fewer lamp changes
- Easy lamp changes with weatherproof clamp and gasket system
- Available in increased heights for inclement weather visibility

General Catalog Numbers

216-□□-□-□□-□□-□

Wattage

30 = 30W*
45 = 45W*

Lamp Type

Q = Quartz
*Not ETL Certified

Colors

C = Clear
Y = Yellow
R = Red
G = Green
B = Blue
O = Opaque

Option

2 = Frangible coupling with 2" thread for 1" dia. column

Overall Height

14 = 14"
20 = 20"
24 = 24"
30 = 30"
Other heights available

Example: 216-45-Q-CY-24 is a 216 fixture with 45 Watt Quartz lamp, clear/yellow lens and 24" overall height



Parts

Head Assemblies

Includes housing, socket, cord, gasket and lens clamp

216Q-XX L-861, L-861T - 1-5/8"
Standoff 99-00305

Quartz

X = Overall height of fixture -14", 20", 24" or 30"- other heights available

Lamp Sockets

73-Q Quartz

Connector Cords

766Q-X Quartz

X = Overall height of fixture -14", 20", 24" or 30"- other heights available


Lenses

| | |
|-----|--------------|
| 50 | Green |
| 51 | Blue |
| 52 | Red |
| 54 | Yellow |
| 249 | Clear |
| 250 | Clear/Green |
| 251 | Clear/Red |
| 252 | Green/Opaque |
| 253 | Green/Yellow |
| 254 | Red/Yellow |
| 255 | Clear/Yellow |
| 256 | Red/Green |

Columns

| | |
|-------|-------------------------------------|
| 77 | 6" (14" overall height of fixture) |
| 78 | 12" (20" overall height of fixture) |
| 78-16 | 16" (24" overall height of fixture) |
| 79 | 22" (30" overall height of fixture) |

Other heights available.



Lamps

| | |
|--------|-------------------|
| 100A | 30W Incandescent* |
| 101A | 45W Incandescent* |
| 100Q | 30W Quartz* |
| 101Q-A | 45W Quartz* |

Accessories

| | |
|-----------|--|
| 34-030666 | L-830-1 30/45W Transformer |
| 82-D4 | L-823 Primary Connector Kit - #8 AWG |
| 71 | L-867B 12" diameter base plate w/ 1.5" hub |
| 72 | L-867B 12" diameter base plate w/ 2" hub |

Other

| | |
|------|--|
| 61 | Lens Clamp |
| 62 | Lens Gasket |
| 58 | Frangible Coupling 1.5" thread for 1" dia. column |
| 58-2 | Frangible Coupling 2" thread for 1" dia. column |

TABLE OF CONTENTS



AirportLightingCompany

An ISO 9001:2015 Certified Company

| | |
|----------------------------------|---|
| How to Get Help | 1 |
| Warranty | 2 |
| Installation Instructions | 2 |
| Maintenance | 2 |
| Notes | 3 |



HOW TO GET HELP



AirportLightingCompany

An ISO 9001:2015 Certified Company

General Inquiry:



PHONE: (315) 682-6460



EMAIL: info@airportlightingcompany.com

Technical Support:




PHONE: (866) 212-1060



EMAIL: support@airportlightingcompany.com



WEBSITE: www.airportlightingcompany.com



AirportLightingCompany

An ISO 9001:2015 Certified Company

**108 Fairgrounds Drive
Manlius, New York 13104**



Warranty

Airport Lighting Company warrants that the equipment has been manufactured and will perform in accordance with applicable specifications and that any defect in design, materials, (excluding lamps), or workmanship which may occur during proper and normal use during a period of 1 year from date of installation or at least 2 years from date of shipment will be corrected by repair or replacement by the manufacturers f.o.b. factory.

Installation Instructions

The fixture ships from Airport Lighting Company ready to be plugged into a 30/45W isolation transformer with a 6.6amp secondary. Install the lamp using care not to let your skin contact the glass of the lamp. Remove the clamp band, install the lens by aligning the notches of the glass with the bosses on the casting, and replace the clamp band. Snake the cord through the column and frangible coupling. Secure the column to the frangible coupling, tightening to 30 in lbs. Plug the fixture into the isolation transformer secondary. Thread the frangible coupling onto the baseplate. If the lens is bidirectional, rotate the fixture until the division between the glass is perpendicular to the pavement. Place a torpedo level along the bottom edge of the light fixture base. Using the (3) 1/4"-20 hex screws in the base of the fixture adjust the screws until the light fixture is level and tighten to 30 in lbs.

Maintenance

As part of the lamp replacement process, wipe the lens clean inside and out. Check that bidirectional fixtures are aligned properly to the pavement.

NOTES



Airport**Lighting**Company

An ISO 9001:2015 Certified Company